

User Information

English translation

Correct Use

The SREC contact block in combination with any basic device from the ZANDER SR series can be used to produce up to three additional safety contact paths per device. An existing system can thus be expanded practically indefinitely in a modular manner. Activation takes place via a safety contact of the basic device, the SREC provides signaling contacts for fault monitoring. The devices can be used in systems up to safety category 4, PL e according to EN ISO 13849-1.



(not for plug-in terminals)

Features

- 3 safe, redundant relay outputs
- 1 auxiliary contact (fault monitoring)
- Activation via basic device from the ZANDER SR series
- Modular, freely configurable safety system
- Fault monitoring by basic device
- Earth fault monitoring
- Indication of the switching state via LED
- Up to PL e, SILCL 3, category 4

Function

The safety expansion contact block SREC in combination with a basic device from the ZANDER SR series is designed for safe isolation of safety circuits according to EN 60204-1 and can be used up to safety category 4, PL e according to EN ISO 13849-1.

Terminal S11 (DC 24V control voltage) is connected with terminals S15 and S16 via the safety contacts of the basic device. Starting the basic device also activates the SREC. The basic device disconnects the control voltage when the safety switch is operated, and the safety contacts of the SREC open immediately.

If a fault occurs in the SREC, this is detected by the basic device via terminals S23 and S24.

Independent operation without basic device is not possible.




Fig. 1 Block diagram SREC

Installation

As per EN 60204-1, the device is intended for installation in control cabinets with a minimum degree of protection of IP54. It is mounted on a 35-mm DIN rail according to DIN EN 60715 TH35.




Fig. 2 Installation / removal


Safety Precautions



- Installation and commissioning of the device must be performed **only by authorized personnel**.
- Observe the country-specific regulations when installing the device.
- The electrical connection of the device is only allowed to be made with the device isolated.
- The wiring of the device must comply with the instructions in this user information, otherwise there is a risk that the safety function will be lost.
- It is not allowed to open the device, tamper with the device or bypass the safety devices.
- All relevant safety regulations and standards are to be observed.
- The overall concept of the control system in which the device is incorporated must be validated by the user.
- Failure to observe the safety regulations can result in death, serious injury and serious damage.

Electrical Connection

- When the 24V version is used, a control transformer according to DIN EN 61558-2-6 or a power supply unit with electrical isolation from the mains must be connected.
- External fusing of the safety contacts (4 A slow-blow or 6 A quick-action or 10 A gG) must be provided.
- A maximum length of the control lines of 1000 meters with a line cross section of 0.75 mm² must not be exceeded.
- The line cross section must not exceed 2.5 mm².
- If the device does not function after commissioning, it must be returned to the manufacturer unopened. Opening the device will void the warranty.
- PE (protective earth) must be connected to terminal S10 on the AC 115/230V variant. Wiring of the overall device is to be designed for 115/230V.



- A1: Power supply
- A2: Power supply
- S11: DC 24V control voltage
- S10: Control line
- S15: Control line
- S16: Control line
- S23: Fault monitoring
- S24: Fault monitoring
- 13-14: Safety contact 1
- 23-24: Safety contact 2
- 33-34: Safety contact 3

Fig. 3 Connections

User Information

Applications

Depending on the application, the device must be wired with a ZANDER basic device as shown in Fig. 1 to Fig. 2. If the devices are wired inside a control cabinet (minimum degree of protection IP54), the fault involving a short circuit between the activation lines can be ruled out (protected wiring space). Category 4, PL e according to EN ISO 13849-1 is thereby possible. If this fault cannot be ruled out, category 3, PL e is achieved.

Wiring




Fig. 1: Connection of SREC to Basic Device

Wiring of the SREC via only 4 lines:

A safety contact of the basic devices (e.g. 13-14) activates the relays of the SREC (S11 and S15/S16).

Two lines on S23 and S24 are required for feedback/fault monitoring. A fault in the SREC thereby prevents the entire safety chain from restarting.

Earth faults in the control lines are detected in addition to internal faults.




Fig. 2: Connection of several SREC Units to Basic Device

If further SREC units are to be integrated into the system, terminals S11 must be connected in parallel on all SREC units. This also applies to terminals S10 and terminals S15/S16.

Notice:

In order to activate earth fault monitoring, S10 must be connected to PE (protective earth) on the AC115/230V devices. With AC/DC 24V, connect PE only to the power supply unit according to EN60204-1.

Feedback Loop




Fig. 3: Feedback Loop

Contacts connected to the SREC or the basic devices are monitored via the feedback loop of the basic device. KA and KB are the positively driven contacts of the connected contactor or expansion module.




Fig. 4: Feedback Loop with Auto-Start

Contacts connected to the SREC or the basic devices are monitored via the feedback loop of the basic device. KA and KB are the positively driven contacts of the connected contactor or expansion module.

Power supply and Safety contacts




Fig. 5:

Power supply A1 and A2.

(Power supply according to techn. Data)




Fig. 6:

Connecting load to safety contacts.

(Figure shows example. Voltage „+V“ according to techn. Data)

Commissioning Procedure

Note: The items listed under “Electrical connection” must be observed during commissioning.

1. Wiring SREC:

Wire the SREC with the ZANDER basic device according to your application (see Fig. 1 to Fig. 2).

2. Wiring basic device:

Wire the basic device according to the required Performance Level determined (see user information for the basic device).

3. Wiring feedback loop:

Wire the feedback loop as shown in Fig. 3 or Fig. 4.

4. Wiring power supply:

Connect the power supply to terminals A1 and A2 (Fig. 5).

Warning: Wiring only in de-energized state.

5. Starting the device:

Switch on the operating voltage.

Warning:

If the “Automatic start” starting behavior is set on the basic device, the safety contacts will close immediately.

If the “Monitored manual start” starting behavior is set, close the start button on the basic device to close the safety contacts.

The LEDs **K1** and **K2** on the basic device and on the SREC are lit.

6. Triggering safety function:

Open the emergency stop circuit by actuating the connected safety switch. The safety contacts of the basic device and the SREC open immediately.

7. Reactivation:

Close the emergency stop circuit. If “Automatic start” is selected on the basic device, the safety contacts will close immediately.

If the “Monitored manual start” starting behavior is set, close the start button on the basic device to close the safety contacts of the basic device and the SREC.



User Information

Maintenance

The device must be checked once per month for proper function and for signs of tampering and bypassing of the safety function.

The device is otherwise maintenance free, provided that it was installed properly.

What to Do in Case of a Fault?

Device does not switch on:

- Check the wiring of the SREC and the basic device by comparing it with the wiring diagrams (also see user information for the basic device).
- Check the safety switch used on the basic device for correct function and adjustment.
- Check whether the emergency stop circuit of the basic device is closed.
- Check whether the start button on the basic device (with manual start) is closed.
- Check the operating voltage at A1 and A2 on the basic device and on the SREC.
- Is the feedback loop closed?

Device cannot be switched on again after an emergency stop:

- Check whether the emergency stop circuit was closed again.
- Was the start button opened before closing of the emergency stop circuit (with manual start)?
- Is the feedback loop closed?
- Is the power supply present during the time sequence?

If the fault still exists, perform the steps listed under "Commissioning Procedure".

If these steps do not remedy the fault either, return the device to the manufacturer for examination.

Opening the device is impermissible and will void the warranty.

Safety Characteristics According to EN ISO 13849-1

The device is certified according to EN ISO 13849-1 up to a Performance Level of PL e.

Note:

Additional data can be requested from the manufacturer for applications that deviate from these conditions.

Safety characteristics according to EN ISO 13849-1 for all variants of SREC			
Load (DC13; 24V)	<= 0,1A	<= 1A	<= 2A
T10d [years]	20	20	20
Category	4	4	4
PL	e	e	e
PFHd [1/h]	1,2E-08	1,2E-08	1,2E-08
nop [cycle / year]	<= 400.000	<= 73.000	<= 17.000

Techn. Data


Corresponds to the standards	EN 60204-1; EN ISO 13849-1 ; EN 62061
Operating voltage	AC 230V, AC 115V, AC/DC 24V, AC: 50-60Hz
Permissible deviation	+ / - 10%
Power consumption	DC 24V AC 230V approx. 1.2 W approx. 3.5 VA
Control voltage at S11	DC 24V
Control current S11...S14	max. 40mA
Safety contacts	3 NO contacts
Auxiliary contacts	1 NC contact; monitoring contact for basic device
Max. switching voltage	AC 250V
Safety contact breaking capacity	AC: 250V, 1.500VA, 6A for ohmic load, 250V, 4A for AC-15 DC: 24V, 30W, 1.25A for ohmic load; 24V, 30W, 2A for DC-13 Max. total current through all 3 contacts: 10.5A
Minimum contact load	24V, 20mA
Min. Contact fuses	4 A slow-blow or 6 A quick-action or 10A gG
Max. line cross section	0.14 - 2.5mm ²
Max. length of control line	1000m with 0.75mm ²
Contact material	AgNi
Contact service life	mech. approx. 1 x 10 ⁷ , electr. 1 x 10 ⁵ operating cycles
Test voltage	2.5kV (control voltage/contacts)
Rated impulse withstand voltage, leakage path/air gap	4kV (DIN VDE 0110-1)
Rated insulation voltage	250V
Degree of protection	IP20
Temperature range	DC 24V: -15°C to +60°C AC 230/115V: -15°C to +40°C
Degree of contamination	2 (DIN VDE 0110-1)
Overvoltage category	3 (DIN VDE 0110-1)
Weight	approx. 230g
Mounting	DIN rail according to EN 60715TH35

B09
B101

E61-142-00

User Information

Dimension Drawing



Variants

Order no. 472180	SREC, AC 230V (50-60Hz), fixed screw terminals
Order no. 472181	SREC, AC 115V (50-60Hz), fixed screw terminals
Order no. 472182	SREC, AC/DC 24V (AC: 50-60Hz), fixed screw terminals
Order no. 473180	SREC, AC 230V (50-60Hz), plug-in terminals
Order no. 473181	SREC, AC 115V (50-60Hz), plug-in terminals
Order no. 473182	SREC, AC/DC 24V (AC: 50-60Hz), plug-in terminals
Order no. 472592	EKLS4, set of plug-in screw terminals
Order no. 472593	EKLZ4, set of plug-in tensile spring terminals

Konformitätserklärung EC Declaration of Conformity



Hersteller: H. ZANDER GmbH & Co. KG
Producer: Am Gut Wolf 15 • D-52070 Aachen

Produktgruppe: Sicherheits-Not-Aus-Schaltgeräte
Product Group: Safety emergency stop switching devices

Die Produkte stimmen mit den Vorschriften folgender Europäischer Richtlinien überein:
The products conform with the essential protection requirements of the following European directives:

2006/42/EG : Maschinenrichtlinie
2006/42/EG : Machinery directive

2004/108/EG : EMV Richtlinie
2004/108/EG : EMC directive

2006/95/EG : Niederspannungsrichtlinie
2006/95/EG : Low voltage switchgear directive

Die Übereinstimmung der bezeichneten Produkte mit den Vorschriften der o.a. Richtlinie wird, falls anwendbar, nachgewiesen durch die vollständige Einhaltung folgender Normen:
If applicable, the conformity of the designated products is proved by full compliance with the following standards:

EN 60439-1:2005-01	EN 60947-1:2008-04	EN 60947-5-1:2005-02
EN 60947-7-1:2003-07	EN 61000-6-2:2006-03	EN 61000-6-3:2005-05
DIN EN 61326-3-1:2008-11	DIN EN ISO 13849-1:2008-12	DIN EN ISO 13849-2:2003
IEC 62061:2005-10		

Produkt Name Product Name	Anbringung der CE-Kennzeichnung Affixing of CE marking:	Zertifikats-Nr. No of Certificate
SRTC	2009	968/EZ 380.00/09
SREC	2010	968/EZ 385.00/09

Produkt Name Product Name	Anbringung der CE-Kennzeichnung Affixing of CE marking:	Zertifikats-Nr. No of Certificate

Benannte Stelle:
TÜV Rheinland Industrie Service GmbH
Geschäftsfeld ASI
Am Grauen Stein
51105 Köln

Dokumentationsbeauftragter: Christiane Nittschalk
(Documentation manager)

Aachen, den 15.12.2009

Dipl.-Ing. Walter Zander
Geschäftsleitung
(General Manager)

Dipl.-Ing. Alfons Austerhoff
Leiter CE-Konformitätsbewertung
(Manager for EC declaration of conformity)

B09
B101

E61-142-00